https://www.eibabo.us/eltako/staircase-light-time-switch-staircase-lighting-timer-1...12min-tlz12-8plus-eb15710342

Staircase light time switch - Staircase lighting timer 1...12min TLZ12-8plus

Eltako
TLZ12-8plus
23100832
4010312401613 EAN/GTIN

39,53 USD excl. VAT**

plus **shipping**

4-5 days* (USA)

Staircase light time switch TLZ12-8plus electronic function with switch-off early warning, mounting type DIN rail, width in modular units 1, installation depth 58mm, number of contacts as NO contact 1, number of contacts as NC contact 0, number of contacts as changeover contact 0, control voltage 1 230 ... 230V , type of control voltage 1 AC, frequency of control voltage 1 50 ... 50Hz, control voltage 2 8 ... 230V, type of control voltage 2 AC/DC, rated switching current 1.6A, release delay 1 ... 12min, button glow lamp current 50mA, switching type 3 and 4 -Conductor circuit, switch-off warning flicker, current surge function selectable, downstream switching + continuous light + time extension, supply voltage 230 ... 230V, voltage type of the supply voltage AC, max. incandescent lamp load 400W, max. fluorescent lamp load (parallel compensated) 400VA, staircase light time switch with switch-off warning and Button permanent light can be switched on. Standby loss only 0.7 watts. With ESL optimization and multifunction. Contact switching in the zero crossing to protect the contacts and lamps. In particular, this extends the life of energy-saving lamps. Due to the use of a bistable relay, there is no coil power loss and no heating as a result, even when switched on. After installation, wait for the brief automatic synchronization before the switched consumer is connected to the mains. Additionally with galvanically isolated universal control voltage. Automatic recognition of the switching type. Glow lamp current up to 50mA, depending on the ignition voltage of the glow lamps. Exact time setting 1 to 30 minutes with minute scale. Permanent light switch with the large rotary switch. After a power failure in the TLZ function setting, the lighting is switched on again if the time has not yet expired. With double connections for button and lamp, so that you can choose to connect at the top and bottom or only at the bottom. When the switch-off pre-warning is switched on, the lighting flickers about 30 seconds before the time expires and a total of 3 times at increasingly shorter intervals. When the button permanent light is switched on, buttons can be used to switch to permanent light for longer than 1 second, which is switched off automatically after 60 minutes or can be switched off with buttons for longer than 2 seconds. If the button permanent light and switch-off pre-warning are switched on, the switch-off pre-warning is only given after the permanent light has been switched off.

YOUR ADVANTAGES

WORLDWIDE TRADE
Corporate video eibmarkt®

99% CUSTOMER SATISFACTION
> 500,000 customers worldwide

DHL TRACK & TRACE
Shipment tracking

COMPLAINTS HANDLING
Obliging and 100% safely

25 YEARS OF EXPERIENCE
In worldwide mail order

ORDER LIVE CHAT
With order history

SHORT DELIVERY TIME
Warehousing

REFUND
Within 14 days

DATA PROTECTION
Guarantee

eibabo® the Smart Home technology shop
eibabo® electronics cheap online order
eibabo® electric appliances buy online